

\*\*\*SPARE PART\*\*\* SIMATIC ET 200SP, ANALOG INPUT MODULE, AI ENERGY METER ST, FITS TO BU-TYPE D0, CHANNEL DIAGNOSIS,



General information	
Product type designation	AI energy meter 400VAC ST
Firmware version	V2.0
usable BaseUnits	BU type D0, BU20-P12+A0+0B
Product function	
• Voltage measurement	Yes
• Voltage measurement with voltage transformers	No
• Current measurement	Yes
• Phase current measurement without current transformers	No
• Phase current measurement with current transformers	Yes
• Energy measurement	Yes
• Frequency measurement	Yes
• Power measurement	Yes
• Active power measurement	Yes
• Reactive power measurement	Yes
• I&M data	Yes; I&M0 to I&M3

• Isochronous mode	No
<b>Engineering with</b>	
• STEP 7 TIA Portal configurable/integrated as of version	V13 SP1
• STEP 7 configurable/integrated as of version	V5.5 SP4 and higher
• PROFIBUS as of GSD version/GSD revision	GSD Revision 5
• PROFINET as of GSD version/GSD revision	V2.3
<b>Operating mode</b>	
• cyclic measurement	Yes
• acyclic measurement	Yes
• Acyclic measured value access	Yes
• Fixed measured value sets	Yes
• Freely definable measured value sets	No
<b>Configuration control</b>	
via dataset	Yes
<b>CiR – Configuration in RUN</b>	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
<b>Installation type/mounting</b>	
Mounting position	Any
<b>Supply voltage</b>	
Design of the power supply	Supply via voltage measurement channel L1
Type of supply voltage	100 - 240 V AC
permissible range, lower limit (AC)	90 V
permissible range, upper limit (AC)	264 V
<b>Line frequency</b>	
• permissible range, lower limit	47 Hz
• permissible range, upper limit	63 Hz
<b>Power loss</b>	
Power loss, typ.	0.6 W
<b>Address area</b>	
Address space per module	
• Address space per module, max.	44 byte; 32 byte input / 12 byte output
<b>Hardware configuration</b>	
Automatic encoding	
• Mechanical coding element	Yes
<b>Time of day</b>	
Operating hours counter	
• present	No

## Analog inputs

Cycle time (all channels), typ.	50 ms; Time for consistent update of all measured and calculated values (cyclic und acyclic data)
---------------------------------	---

## Interrupts/diagnostics/status information

### Alarms

• Diagnostic alarm	Yes
• Limit value alarm	No
• Hardware interrupt	No

### Diagnostics indication LED

• Monitoring of the supply voltage (PWR-LED)	Yes
• Channel status display	Yes; Green LED
• for channel diagnostics	Yes; red Fn LED
• for module diagnostics	Yes; green/red DIAG LED

## Integrated Functions

### Measuring functions

• Measuring procedure for voltage measurement	TRMS
• Measuring procedure for current measurement	TRMS
• Type of measured value acquisition	seamless
• Curve shape of voltage	Sinusoidal or distorted
• Buffering of measured variables	No
• Parameter length	38 byte
• Bandwidth of measured value acquisition	2 kHz; Harmonics: 39 / 50 Hz, 32 / 60 Hz

### Operating mode for measured value acquisition

— automatic detection of line frequency	No; Parameterizable
---	---------------------

### Measuring range

— Frequency measurement, min.	45 Hz
— Frequency measurement, max.	65 Hz

### Measuring inputs for voltage

— Measurable line voltage between phase and neutral conductor	230 V
— Measurable line voltage between the line conductors	400 V
— Measurable line voltage between phase and neutral conductor, min.	90 V
— Measurable line voltage between phase and neutral conductor, max.	264 V
— Measurable line voltage between the line conductors, min.	155 V
— Measurable line voltage between the line conductors, max.	460 V

— Measurement category for voltage measurement in accordance with IEC 61010-2-030	CAT II; CAT III in case of guaranteed protection level of 1.5 kV
— Internal resistance line conductor and neutral conductor	3.4 MΩ
— Power consumption per phase	20 mW
— Impulse voltage resistance 1,2/50μs	1 kV

#### Measuring inputs for current

— measurable relative current (AC), min.	5 %; Relative to the secondary rated current; 1 A, 5 A
— measurable relative current (AC), max.	100 %; Relative to the secondary rated current; 1 A, 5 A
— Continuous current with AC, maximum permissible	5 A
— Apparent power consumption per phase for measuring range 5 A	0.6 V·A
— Rated value short-time withstand current restricted to 1 s	100 A
— Input resistance measuring range 0 to 5 A	25 mΩ
— Zero point suppression	Parameterizable: 20 - 250 mA, default 50 mA
— Surge strength	10 A; for 1 minute

#### Accuracy class according to IEC 61557-12

— Measured variable voltage	0.5
— Measured variable current	0.5
— Measured variable apparent power	1
— Measured variable active power	1
— Measured variable reactive power	1
— Measured variable power factor	0.5
— Measured variable active energy	1
— Measured variable reactive energy	2
— Measured variable phase angle	±1 °; not covered by IEC 61557-12
— Measured variable frequency	0.05

#### Potential separation

##### Potential separation channels

- between the channels and backplane bus Yes; 3 700V AC (type test) CAT III

#### Isolation

Isolation tested with 2 300V AC for 1 min. (type test)

#### Ambient conditions

##### Ambient temperature during operation

- horizontal installation, min. 0 °C
- horizontal installation, max. 60 °C
- vertical installation, min. 0 °C
- vertical installation, max. 50 °C

## Dimensions

Width	20 mm
Height	73 mm
Depth	58 mm

## Weights

Weight (without packaging)	45 g
----------------------------	------

## Other

### Data for selecting a current transformer

- Burden power current transformer  $x/1A$ , min. As a function of cable length and cross section, see device manual
- Burden power current transformer  $x/5A$ , min. As a function of cable length and cross section, see device manual

**last modified:** 03/07/2017