## **SIEMENS**

## Data sheet

## 6EP1931-2DC42

SITOP DC UPS MODULE 6A WITH USB INTERF. SITOP DC UPS module 24 V/6 A uninterruptible power supply with USB interface input: 24 V DC/6.85 A output: 24 V DC/6 A



| nput  |   |
|---|---|
| Supply voltage at DC Rated value                                  | 24 V  |
| Voltage curve at input  | DC  |
| input voltage range   | 22 29 V DC  |
| Adjustable response value voltage for buffer<br>connection preset | 22.5 V  |
| Adjustable response value voltage for buffer connection           | 22 25.5 V; Adjustable in 0.5 V increments   |
| Input current at rated input voltage 24 V Rated value             | 6 A; + approx. 0.6 A with empty battery   |
| Mains buffering   |   |
| Type of energy storage  | with batteries  |
| Design of the mains power cut bridging-connection                 | Dependent on connected battery and load current, see selection                                      |
|   | table battery module and mains buffering times as well as the relevant important information notes! |
| Charging current  |   |
| Charging current <ul> <li>1</li> </ul>                            |   |
| •••   | relevant important information notes!   |

Output

| 24 V   |
|--|
| 24 V   |
| Vin - approx. 0.5 V  |
| 1s   |
| 60 ms  |
| 19 28.5 V  |
|  |
| 6 A  |
| 0 6 A  |
| 0 6 A  |
| 6.3 A  |
| Yes  |
| 144 W  |
|  |
|  |
| 95 %   |
| 94.5 %   |
|  |
| 7 W  |
| 8 W  |
|  |
|  |
| Yes  |
| Yes  |
|  |
|  |
| Normal operation: LED green (OK), floating changeover contact<br>"Bat/OK" to setting "OK" ("OK" means: Voltage of the supplying<br>power supply unit is greater than cut-in threshold set at the DC<br>UPS module); Lack of buffer standby: LED red (alarm), floating<br>changeover contact "Alarm/Bat" to setting "Alarm"; Battery<br>replacement required: LED red (alarm) flashing with approx. 0.25<br>Hz, floating changeover contact "Alarm/Bat" switching with<br>approx. 0.25 Hz; Energy storage > 85%: LED green (Bat > 85%), |
|  |

• in buffering mode

Buffered mode: LED yellow (Bat), floating changeover contact "OK/Bat" to setting "Bat"; Prewarning battery voltage < 20.4 VDC: LED red (alarm), floating changeover contact "Alarm/Bat" to setting "Alarm"; Energy storage > 85%: LED green (Bat > 85%), floating NO contact "Bat > 85" closed

| Interface                                      |   |
|--|---|
| Product component PC interface                 | Yes   |
| Design of the interface                        | USB   |
| Safety   |   |
| Galvanic isolation between entrance and outlet | No  |
| Operating resource protection class            | Class III   |
| Certificate of suitability                     |   |
| • CE marking                                   | Yes   |
| <ul> <li>as approval for USA</li> </ul>        | cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259      |
| <ul> <li>relating to ATEX</li> </ul>           | -   |
| • C-Tick                                       | No  |
| Shipbuilding approval                          | GL, ABS   |
| Protection class IP                            | IP20  |
|  |   |
| EMC<br>Standard                                |   |
| for emitted interference                       | EN 55022 Class B  |
|  | EN 61000-6-2  |
| for interference immunity                      | LIN 01000-0-2   |
| Operating data                                 |   |
| Ambient temperature                            |   |
| <ul> <li>during operation</li> </ul>           | -25 +60 °C; with natural convection                           |
| <ul> <li>during transport</li> </ul>           | -40 +85 °C  |
| • during storage                               | -40 +85 °C  |
| Environmental category acc. to IEC 60721       | Climate class 3K3, no condensation                            |
| Mechanics                                      |   |
| Type of electrical connection                  | screw-type terminals  |
| ● at input                                     | 24 V DC: 2 screw terminals for 1 4 mm <sup>2</sup> /17 11 AWG |
| • at output                                    | 24 V DC: 4 screw terminals for 1 4 mm²/17 11 AWG              |
| <ul> <li>for battery module</li> </ul>         | 24 V DC: 2 screw terminals for 1 4 mm²/17 11 AWG              |
| • for control circuit and status message       | 10 screw terminals for 0.5 2.5 mm²/20 13 AWG                  |
| Width of the enclosure                         | 50 mm   |
| Height of the enclosure                        | 125 mm  |
| Depth of the enclosure                         | 125 mm  |
| Required spacing                               |   |
| • top  | 50 mm   |
| • bottom                                       | 50 mm   |
| • left   | 0 mm  |
|  |   |

| ● right  | 0 mm  |
|--|---|
| Net weight   | 0.45 kg   |
| Product feature of the enclosure housing for side-by-<br>side mounting | Yes   |
| Mounting type  | Snaps onto DIN rail EN 60715 35x7.5/15  |
| Electrical accessories   | Battery module  |
| MTBF at 40 °C  | 904 159 h   |
| Equipment marking acc. to DIN EN 81346-2                               | т   |
| Other information  | Specifications at rated input voltage and ambient temperature +25 °C (unless otherwise specified) |