

Product type designation

Power Supply PS791-2DC

Power-Supply PS 791-2DC, DC/DC power supply 10 W, IP65 - 40...+70° C, Input: DC 12...24V, Output: DC 18 V, usable only in combination with SCALANCE W-786; scope of supply: manual, German/English



Type of current supply	10 W, input: 12-24 V DC, output:18 V DC
Electrical data / Input	
Supply voltage / 1 / Rated value	12 V
• Supply voltage / 1 / rated value	9 ... 32 V
• Type of voltage / 1 / of the supply voltage	DC, safety extra-low voltage (SELV)
Supply voltage / 2 / Rated value	24 V
• Supply voltage / 2 / rated value	9 ... 32 V
• Type of voltage / 2 / of the supply voltage	DC, safety extra-low voltage (SELV)
Buffering time / at rated output current / in the event of power failure / minimum	14,4
Electrical data / Output	
Output voltage / at DC / Rated value	18 V
Supplied active power / typical	14.4 W
Electrical data / Safety	
Operating resource protection class	VDE 0805, VDE 0100
Interfaces	
Type of electrical connection	

- at input
- at output

4-pole screw-type terminal for DC power
4 pin connector

Design, dimensions and weight

Width	133 mm
Height	45 mm
Depth	30 mm
Net weight	0.223 kg

Permitted ambient conditions

Ambient temperature	
<ul style="list-style-type: none"> • during operation 	-40 ... +70 °C
Protection class IP	IP65

Standards, specifications, approvals

Standard	
<ul style="list-style-type: none"> • for safety / from CSA and UL 	EN 60950, UL 60950-1

Further Information / Internet Links

Internet-Link	
<ul style="list-style-type: none"> • to website: Selector SIMATIC NET SELECTION TOOL • to website: Industrial communication • to website: Industry Mall • to website: Information and Download Center • to website: Image database • to website: CAx Download Manager • to website: Industry Online Support 	<p>http://www.siemens.com/snst</p> <p>http://www.siemens.com/simatic-net</p> <p>https://mall.industry.siemens.com</p> <p>http://www.siemens.com/industry/infocenter</p> <p>http://automation.siemens.com/bilddb</p> <p>http://www.siemens.com/cax</p> <p>https://support.industry.siemens.com</p>

last modified:

06/15/2017