

SIMATIC S7-300, SIMULATOR MODULE SM 374, FOR SIMULATING 16 INPUTS OR 16 OUTPUTS RESP. 8 INPUTS AND 8 OUTPUTS; 16 SWITCHES, 16 LED



Input current	
from backplane bus 5 V DC, max.	80 mA
Power loss	
Power loss, typ.	0.35 W
Digital inputs	
Number of digital inputs	16; Switch
Digital outputs	
Number of digital outputs	16; LEDs
Analog inputs	
Number of analog inputs	0
Analog outputs	
Number of analog outputs	0
Potential separation	
Potential separation digital inputs	
<ul style="list-style-type: none"> between the channels and backplane bus 	No
Potential separation digital outputs	

- between the channels and backplane bus

No

Dimensions

Width	40 mm
Height	125 mm
Depth	120 mm

Weights

Weight, approx. 190 g

last modified: 03/24/2017