# **SIEMENS**

Data sheet 6NH7800-4AA30

# Product type designation

# SIEMENS STATE TOO SEE WHY A SEE SO TO SEE SO TO SEE SINAUT STATE STATE SINAUT STATE SINAUT STATE STAT

## **TIM 43**

SINAUT ST7, TIM 43 COMMUNICATIONS PROCESSOR FOR SIMATIC S7-300/S7-400 WITH MPI INTERFACE WITH RS232/RS485 INTERFACE FOR EXT. MODEM/RADIO DEVICE WITH INT. MODEM MD3 FOR ANALOG SWITCHED NETWORKS

Transmission rate	
Transfer rate	
● acc. to RS 232	50 38400 bit/s
Interferen	
Interfaces	
Number of interfaces / acc. to Industrial Ethernet	0
Type of electrical connection	
<ul><li>for power supply</li></ul>	4-pole terminal block
Supply voltage, current consumption, power loss	
Supply voltage	24 V
Supply voltage / external / at DC / Rated value	24 V
Consumed current	
<ul> <li>from backplane bus / at DC / at 5 V / typical</li> </ul>	0.06 A
<ul><li>from backplane bus / at DC / at 24 V /</li></ul>	0.06 A
maximum	
Power loss [W]	12.3 W
Permitted ambient conditions	
Ambient temperature	

<ul><li>during operation</li></ul>	0 60 °C
during storage	-40 +70 °C
<ul> <li>during transport</li> </ul>	-40 +70 °C
Protection class IP	IP20

Design, dimensions and weight		
Module format	Compact module S7-300 double width	
Width	80 mm	
Height	125 mm	
Depth	120 mm	
Net weight	0.3 kg	

Performance data / BACnet		
Storage capacity / of S7 CPU RAM / required	20 Kibyte	
Performance data / telecontrol		
Suitability for use		
Node station	Yes	
• substation	Yes	
TIM control center	Yes	
Protocol / is supported		
• TCP/IP	No	
<ul> <li>SINAUT ST1 protocol</li> </ul>	Yes	
<ul> <li>SINAUT ST7 protocol</li> </ul>	Yes	
Transmission format		
• for SINAUT ST1 protocol with polling / 11 bit	Yes	
<ul> <li>for SINAUT ST1 protocol with spontaneous / 10-bit or 11-bit</li> </ul>	Yes	
<ul> <li>for SINAUT ST7 protocol with multi-master polling / 10-bit</li> </ul>	Yes	
<ul> <li>for SINAUT ST7 protocol with polling or spontaneous / 10-bit or 11-bit</li> </ul>	Yes	
Operating mode for scanning of data transmission		
<ul> <li>with dedicated line/radio link / with SINAUT ST1 protocol</li> </ul>	Polling, polling with time slot procedure	
<ul> <li>with dedicated line/radio link / with SINAUT ST7 protocol</li> </ul>	Polling, polling with time slot procedure, multi-master polling with time slot procedure	
<ul> <li>with dial-up network / with SINAUT ST1 protocol</li> </ul>	spontaneous	
<ul> <li>with dial-up network / with SINAUT ST7 protocol</li> </ul>	spontaneous	
Configuration software		
<ul> <li>for CPU configuring / required / SINAUT TD7 block library for CPU</li> </ul>	Yes	

 for PG configuring / required / SINAUT ST7 configuration software for PG Yes

### Accessories

# Further Information / Internet Links

### Internet-Link

• to website: Selector SIMATIC NET SELECTION TOOL

• to website: Industrial communication

• to website: Industry Mall

• to website: Information and Download Center

• to website: Image database

• to website: CAx Download Manager

• to website: Industry Online Support

http://www.siemens.com/snst

http://www.siemens.com/simatic-net

https://mall.industry.siemens.com

http://www.siemens.com/industry/infocenter

http://automation.siemens.com/bilddb

http://www.siemens.com/cax

https://support.industry.siemens.com

### Security information

Security information

Siemens provides products and solutions with industrial security functions that support the secure operation of plants, solutions, machines, equipment and/or networks. They are important components in a holistic industrial security concept. With this in mind, Siemens' products and solutions undergo continuous development. Siemens recommends strongly that you regularly check for product updates. For the secure operation of Siemens products and solutions, it is necessary to take suitable preventive action(e.g. cell protection concept) and integrate each component into a holistic, state-of-the-art industrial security concept. Thirdparty products that may be in use should also be considered. For more information about industrial security, visit http://www.siemens.com/industrialsecurity. To stay informed about product updates as they occur, sign up for a product-specific newsletter. For more information, visit http://support.automation.siemens.com. (V3.4)

last modified:

08/18/2017