# **SIEMENS**

# Data sheet

# 6GK5004-1BF00-1AB2

## Product type designation



#### **SCALANCE XB004-1LD**

SCALANCE XB004-1LD UNMANAGED INDUSTRIAL ETHERNET SWITCH FOR 10/100MBIT/S; WITH 4 X 10/100MBIT/S TWISTED PAIR- PORTS WITH RJ45-SOCKETS; 1 X100MBIT/S SINGLEMODE GLASS FOC-PORT WITH SC-SOCKET; FOR CONFIGURING SMALL STAR- AND LINE TOPOGRAPHIES; LEDDIAGNOSIS, IP20, 24 V DC POWER SUPPLY, MANUAL AVAILABLE AS DOWNLOAD

Transmission rate		
Transfer rate	10 Mbit/s, 100 Mbit/s	
Interfaces / for communication / integrated		
Number of electrical connections		
<ul> <li>for network components or terminal equipment</li> </ul>	4; RJ45	
Number of 100 Mbit/s SC ports		
• for multimode	0	
• for single mode (LD)	1	
Number of 1000 Mbit/s LC ports		
• for multimode	0	
• for single mode (LD)	0	
Interfaces / others		
Number of electrical connections		
• for power supply	1	
Type of electrical connection		
• for power supply	3-pole terminal block	
Supply voltage, current consumption, power loss		

Type of voltage / of the supply voltage	AC/DC
Supply voltage	
• external	24 V
• external	19.2 28.8 V
• at AC	24 V
Product component / fusing at power supply input	Yes
Fuse protection type / at input for supply voltage	0.6 A / 60 V
Consumed current / maximum	0.1 A
Power loss [W]	
• at DC / at 24 V	2.4 W
Permitted ambient conditions	
Ambient temperature	
during operation	-10 +60 °C
<ul><li>during storage</li></ul>	-40 +80 °C
during transport	-40 +80 °C
Relative humidity	
<ul> <li>at 25 °C / without condensation / during operation / maximum</li> </ul>	95 %
Protection class IP	IP20
Design, dimensions and weight	
Design	Box
Width	45 mm
Height	100 mm
Depth	87 mm
Net weight	0.165 kg
Mounting type	
• 35 mm DIN rail mounting	Yes
<ul><li>wall mounting</li></ul>	Yes
• S7-1500 rail mounting	No
Product functions / management, configuration	
Product function	N.
multiport mirroring	No 
• CoS	Yes
switch-managed	No
Product functions / Redundancy	
Product function	
<ul> <li>Parallel Redundancy Protocol (PRP)/operation in the PRP-network</li> </ul>	Yes
<ul> <li>Parallel Redundancy Protocol</li> <li>(PRP)/Redundant Network Access (RNA)</li> </ul>	No
Standards, specifications, approvals	
approvato	

Standard	
• for FM	FM3611: Class 1, Divison 2, Group A, B, C, D / T4, CL.1, Zone 2, GP. IIC, T4
• for hazardous zone	EN 60079-0:2009, EN60079-15:2010, II 3 G Ex nA IIC T4 Gc, KEMA 07ATEX0145 X
<ul><li>for safety / from CSA and UL</li></ul>	UL 60950-1, CSA C22.2 No. 60950-1
• for emitted interference	EN 61000-6-4 (Class A)
• for interference immunity	EN 61000-6-2
Certificate of suitability / CE marking	Yes
Certificate of suitability	EN 61000-6-2, EN 61000-6-4
• C-Tick	Yes
<ul> <li>KC approval</li> </ul>	Yes
MTBF / at 40 °C	238 y

## Further Information / Internet Links

#### Internet-Link

• to website: Selector SIMATIC NET SELECTION TOOL

• to website: Industrial communication

• to website: Industry Mall

• to website: Information and Download Center

• to website: Image database

• to website: CAx Download Manager

• to website: Industry Online Support

http://www.siemens.com/snst

http://www.siemens.com/simatic-net

https://mall.industry.siemens.com

http://www.siemens.com/industry/infocenter

http://automation.siemens.com/bilddb

http://www.siemens.com/cax

https://support.industry.siemens.com

## Security information

Security information

Siemens provides products and solutions with industrial security functions that support the secure operation of plants, solutions, machines, equipment and/or networks. They are important components in a holistic industrial security concept. With this in mind, Siemens' products and solutions undergo continuous development. Siemens recommends strongly that you regularly check for product updates. For the secure operation of Siemens products and solutions, it is necessary to take suitable preventive action(e.g. cell protection concept) and integrate each component into a holistic, state-of-the-art industrial security concept. Third-party products that may be in use should also be considered. For more information about industrial security, visit http://www.siemens.com/industrialsecurity. To stay informed about product updates as they occur, sign up for a product-specific newsletter. For more information, visit

http://support.automation.siemens.com. (V3.4)

**last modified:** 06/13/2017